# POWER PRESS 2

## GRUPPI DI SOLLEVAMENTO COMANDATI DA INVERTER A PASSAGGIO D'ACQUA

Gruppi di sollevamento composti da due elettropompe completi di: inverter E-Power, basamento, collettori di aspirazione e mandata, pannello fissaggio quadro, valvole di ritegno, valvole a sfera con bocchettone sferabok 100, pressostati, Manometro.

## *PRESSURE BOOSTER SYSTEM PILOTED BY WATER COOLED INVERTER*

*Pressure booster system with two electric pumps complete with: inverter E-Power, base support, suction and delivery manifolds, electrical panel support, check valves, ball valves with filler 100 sferabok, pressure switcher, pressure gauges.*



Nota: tutti i gruppi sono controllati minuziosamente e collaudati con acqua prima della consegna al cliente, ed hanno regolare certificazione. I componenti utilizzati per l'assemblaggio sono sempre di alta qualità e possono variare a discrezione del produttore. I vasi di espansione non sono compresi nel costo del gruppo.
*Note: all booster systems are accurately checked and tested with water before each delivery with regular certification. The components used are always of high quality and could change according to manufacturer's choise. The pressure tank is not included in the booste system.*

### POWER PRESS 2 1~230V

POWER PRESS 2 - GRUPPI PRESSIONE CON 2 POMPE COMANDATI DA INVERTER
*POWER PRESS 2 - PRESSURE BOOSTER SYSTEM FOR TWO ELECTRIC PUMPS WITH INVERTER CONTROL*

| Modello e codice *Model and code* | | Aliment. Rete *Grid power supply* | Aliment. Pompe *Pumps power supply* | Assorbimento *Current* A | Potenza *Power* kW | Portata - *Flowrate* Q (m³/h) l/min | 0 | 40 | 80 | 120 | 160 | 200 | 240 | 280 | 320 | 360 | 400 | 440 | 480 | 520 | 560 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | | | | | | m3/h | 0 | 2.4 | 4.8 | 7.2 | 9.6 | 12 | 14.4 | 16.8 | 19.2 | 21.6 | 24 | 26.4 | 28.8 | 31.2 | 33.6 |
| | | | | | | Prevalenza - *Head* H (m) | | | | | | | | | | | | | | | |
| **MULTI EVINOX** | | | | | | | | | | | | | | | | | | | | | |
| POWER 2-EVINOX 15P-3M | | 1x230V | 1x230V | 2x 2,8A | 2x 0,4kW | | | 28 | 26 | 22 | 18 | 10 | | | | | | | | | |
| POWER 2-EVINOX 15P-4M | | 1x230V | 1x230V | 2x 3,5A | 2x 0,6kW | | | 35 | 32 | 28 | 22 | 15 | | | | | | | | | |
| POWER 2-EVINOX 15P-5M | | 1x230V | 1x230V | 2x 4,1A | 2x 0,8kW | | | 45 | 43 | 32 | 28 | | | | | | | | | | |
| **VPM** | | | | | | | | | | | | | | | | | | | | | |
| POWER 2-VMP 20P-3 M | | 1x230V | 1x230V | 2x 3,6A | 2x 0,6kW | | | 34 | 32 | 29 | 25 | 20 | 15 | 9 | | | | | | | |
| POWER 2-VMP 20P-4 M | | 1x230V | 1x230V | 2x 4,9A | 2x 0,8kW | | | 46 | 43 | 39 | 34 | 28 | 21 | 12 | | | | | | | |
| POWER 2-VMP 20P-5 M | | 1x230V | 1x230V | 2x 6,0A | 2x 0,9kW | | | 60 | 53 | 49 | 43 | 35 | 26 | 18 | | | | | | | |
| **EVEN PLAST** | | | | | | | | | | | | | | | | | | | | | |
| POWER 2-EVEN PLAST 30-3M | | 1x230V | 1x230V | 2x 2,4A | 2x 0,4kW | | | 32 | 28 | 21 | 14 | | | | | | | | | | |
| POWER 2-EVEN PLAST 30-4M | | 1x230V | 1x230V | 2x 3,5A | 2x 0,5kW | | | 43 | 38 | 30 | 18 | | | | | | | | | | |
| POWER 2-EVEN PLAST 50-3M | | 1x230V | 1x230V | 2x 3,9A | 2x 0,6kW | | | 40 | 38 | 35 | 30 | 27 | 21 | 16 | | | | | | | |
| POWER 2-EVEN PLAST 50-4M | | 1x230V | 1x230V | 2x 5,3A | 2x 0,8kW | | | 54 | 51 | 47 | 41 | 37 | 30 | 22 | | | | | | | |
| POWER 2-EVEN PLAST 80-3M | | 1x230V | 1x230V | 2x 3,9A | 2x 0,6kW | | | 37 | 36 | 34 | 31 | 33 | 28 | 25 | 21 | 18 | 15 | 10 | | | |
| POWER 2-EVEN PLAST 80-4M | | 1x230V | 1x230V | 2x 5,3A | 2x 0,8kW | | | 50 | 48 | 46 | 45 | 41 | 38 | 34 | 30 | 25 | 19 | 14 | | | |





### POWER PRESS 2 1~230V

POWER PRESS 2 - GRUPPI PRESSIONE CON 2 POMPE COMANDATI DA INVERTER
*POWER PRESS 2 - PRESSURE BOOSTER SYSTEM FOR TWO ELECTRIC PUMPS WITH INVERTER CONTROL*

| Modello e codice *Model and code* | | Aliment. Rete *Grid power supply* | Aliment. Pompe *Pumps power supply* | Assorbimento *Current* A | Potenza *Power* kW | Portata - *Flowrate* Q (m³/h) l/min | 0 | 40 | 80 | 120 | 160 | 200 | 240 | 280 | 320 | 360 | 400 | 440 | 480 | 520 | 560 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | | | | | | m3/h | 0 | 2.4 | 4.8 | 7.2 | 9.6 | 12 | 14.4 | 16.8 | 19.2 | 21.6 | 24 | 26.4 | 28.8 | 31.2 | 33.6 |
| | | | | | | Prevalenza - *Head* H (m) | | | | | | | | | | | | | | | |
| **EVEN CAST** | | | | | | | | | | | | | | | | | | | | | |
| POWER 2-EVEN CAST 30-3M | | 1x230V | 1x230V | 2x 2,4A | 2x 0,4kW | | | 32 | 28 | 21 | 14 | | | | | | | | | | |
| POWER 2-EVEN CAST 30-4M | | 1x230V | 1x230V | 2x 3,5A | 2x 0,5kW | | | 43 | 38 | 30 | 18 | | | | | | | | | | |
| POWER 2-EVEN CAST 30-5M | | 1x230V | 1x230V | 2x 3,9A | 2x 0,6kW | | | 50 | 42 | 34 | 22 | | | | | | | | | | |
| POWER 2-EVEN CAST 50-3M | | 1x230V | 1x230V | 2x 3,9A | 2x 0,6kW | | | 40 | 38 | 35 | 30 | 27 | 21 | 16 | | | | | | | |
| POWER 2-EVEN CAST 50-4M | | 1x230V | 1x230V | 2x 5,3A | 2x 0,8kW | | | 54 | 51 | 47 | 41 | 37 | 30 | 22 | | | | | | | |
| POWER 2-EVEN CAST 50-5M | | 1x230V | 1x230V | 2x 6,3A | 2x 1,0kW | | | 67 | 63 | 59 | 51 | 44 | 34 | 25 | | | | | | | |
| POWER 2-EVEN CAST 80-3M | | 1x230V | 1x230V | 2x 3,9A | 2x 0,6kW | | | 37 | 36 | 34 | 31 | 33 | 28 | 25 | 21 | 18 | 15 | 10 | | | |
| POWER 2-EVEN CAST 80-4M | | 1x230V | 1x230V | 2x 5,3A | 2x 0,8kW | | | 50 | 48 | 46 | 45 | 41 | 38 | 34 | 30 | 25 | 19 | 14 | | | |
| POWER 2-EVEN CAST 80-5M | | 1x230V | 1x230V | 2x 6,3A | 2x 1,0kW | | | 60 | 58 | 56 | 55 | 51 | 46 | 42 | 37 | 31 | 24 | 16 | | | |
| **EVEN INOX** | | | | | | | | | | | | | | | | | | | | | |
| POWER 2-EVEN INOX 30-3M | | 1x230V | 1x230V | 2x 2,4A | 2x 0,4kW | | | 32 | 28 | 21 | 14 | | | | | | | | | | |
| POWER 2-EVEN INOX 30-4M | | 1x230V | 1x230V | 2x 3,5A | 2x 0,5kW | | | 43 | 38 | 30 | 18 | | | | | | | | | | |
| POWER 2-EVEN INOX 30-5M | | 1x230V | 1x230V | 2x 3,9A | 2x 0,6kW | | | 50 | 42 | 34 | 22 | | | | | | | | | | |
| POWER 2-EVEN INOX 50-3M | | 1x230V | 1x230V | 2x 3,9A | 2x 0,6kW | | | 40 | 38 | 35 | 30 | 27 | 21 | 16 | | | | | | | |
| POWER 2-EVEN INOX 50-4M | | 1x230V | 1x230V | 2x 5,3A | 2x 0,8kW | | | 54 | 51 | 47 | 41 | 37 | 30 | 22 | | | | | | | |
| POWER 2-EVEN INOX 50-5M | | 1x230V | 1x230V | 2x 6,3A | 2x 1,0kW | | | 54 | 51 | 47 | 41 | 37 | 30 | 22 | | | | | | | |
| POWER 2-EVEN INOX 80-3M | | 1x230V | 1x230V | 2x 3,9A | 2x 0,6kW | | | 37 | 36 | 34 | 31 | 33 | 28 | 25 | 21 | 18 | 15 | 10 | | | |

### POWER PRESS 2 3~400V

POWER PRESS 2 - GRUPPI PRESSIONE CON 2 POMPE COMANDATI DA INVERTER
*POWER PRESS 2 - PRESSURE BOOSTER SYSTEM FOR TWO ELECTRIC PUMPS WITH INVERTER CONTROL*

| Modello e codice *Model and code* | | Aliment. Rete *Grid power supply* | Aliment. Pompe *Pumps power supply* | Assorbimento *Current* A | Potenza *Power* kW | Portata - *Flowrate* Q (m³/h) l/min | 0 | 40 | 80 | 120 | 160 | 200 | 240 | 280 | 320 | 360 | 400 | 440 | 480 | 520 | 560 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | | | | | | m3/h | 0 | 2.4 | 4.8 | 7.2 | 9.6 | 12 | 14.4 | 16.8 | 19.2 | 21.6 | 24 | 26.4 | 28.8 | 31.2 | 33.6 |
| | | | | | | Prevalenza - *Head* H (m) | | | | | | | | | | | | | | | |
| **TWIN 3~400V** | | | | | | | | | | | | | | | | | | | | | |
| POWER 2-TWIN 15 MT | | 1x230V | 3x230V | 2x 4,3 | 2x 1,1 | | | 52 | 51 | 51 | 50 | 48 | 45 | 41 | 40 | 34 | 32 | 28 | 21 | | |
| POWER 2-TWIN 20 MT | | 1x230V | 3x230V | 2x 5,0 | 2x 1,5 | | | 58 | 57 | 55 | 54 | 52 | 50 | 48 | 45 | 42 | 38 | 34 | 28 | 22 | |
| **MULTI-EVINOX 3~400V** | | | | | | | | | | | | | | | | | | | | | |
| POWER 2-MULTI EVINOX 35P-4MT | | 1x230V | 3x230V | 2x 6,9A | 2x 1,8kW | | | 51 | 49 | 48 | 46 | 44 | 41 | 39 | 35 | 31 | 26 | 20 | | | |
| POWER 2-MULTI EVINOX 35P-5 MT | | 1x230V | 3x230V | 2x 8,3A | 2x 2,2kW | | | 56 | 55 | 54 | 54 | 53 | 51 | 49 | 48 | 46 | 42 | 38 | 34 | 32 | |
| **VPM 3~400V** | | | | | | | | | | | | | | | | | | | | | |
| POWER 2-VMP 25P-5 MT | | 1x230V | 3x230V | 2x 4,7A | 2x 1,1kW | | | 51 | 49 | 48 | 46 | 44 | 41 | 39 | 35 | 31 | 26 | 20 | | | |
| POWER 2-VMP 35 4MT | | 1x230V | 3x230V | 2x 6,9A | 2x 1,8kW | | | 56 | 55 | 54 | 54 | 53 | 51 | 49 | 48 | 46 | 42 | 38 | 34 | 32 | |
| POWER 2-VMP 35 5MT | | 1x230V | 3x230V | 2x 8,3A | 2x 2,2kW | | | 73 | 73 | 72 | 71 | 69 | 66 | 65 | 60 | 58 | 56 | 50 | 47 | 40 | |
| **EVEN INOX 3~400V** | | | | | | | | | | | | | | | | | | | | | |
| POWER 2-EVEN INOX 50-4MT | | 1x230V | 3x400V | 2x 1,9A | 2x 0,8kW | | | 54 | 51 | 47 | 41 | 37 | 30 | 22 | | | | | | | |
| POWER 2-EVEN INOX 50-5MT | | 1x230V | 3x400V | 2x 2,6A | 2x 1,0kW | | | 67 | 63 | 59 | 51 | 44 | 34 | 25 | | | | | | | |
| POWER 2-EVEN INOX 80-4MT | | 1x230V | 3x230V | 2x 3,5A | 2x 0,8kW | | | 50 | 48 | 46 | 45 | 41 | 38 | 34 | 30 | 25 | 19 | 14 | | | |
| POWER 2-EVEN INOX 80-5MT | | 1x230V | 3x230V | 2x 4,2A | 2x 1,0kW | | | 60 | 58 | 56 | 55 | 51 | 46 | 42 | 37 | 31 | 24 | 16 | | | |